

# TECHNICAL BULLETIN

[Issue No.] FA-A-0091-F

[Page] 2/24

[Title] Products compatible with Windows 7 and precautions for installation

[Date of Issue] June 2010 (Ver.F: January 2012)

[Relevant Models] Mitsubishi integrated FA software MELSOFT series  
GX series, MX series, PX series, GT series

## 1. List of Windows® 7-compatible products

The products shown below are compatible with Windows® 7.

For installation procedure, refer to the section in the "Reference" column.

### (1) Windows® 7 (32-bit) compatible products

Product *1	Japanese Version		English Version		Reference	Remarks
	S/W Version	DATE of CD-ROM or DVD-ROM *2	S/W Version	DATE of CD-ROM or DVD-ROM *2		
iQ Works	1.15R and later	1007CR and later	1.16S and later	1010CS and later	Section 2.1	
GX Works2	1.34L and later	1006BL and later	1.40S and later	1009BS and later		
GX Developer	8.91V and later	1005BV and later	8.91V and later	1005BV and later		
GX Configurator-AD	2.11M and later	0911BM and later	2.11M and later	1001BM and later		*3
GX Configurator-DA	2.11M and later	0911BM and later	2.11M and later	1001BM and later		*3
GX Configurator-CT	1.29AF and later	1001BF and later	1.29AF and later	1003BF and later		*3
GX Configurator-TC	1.24AA and later	0806BA, 0807BA and later	1.24AA and later	0806BA, 0807BA and later		*3
GX Configurator-TI	1.28AE and later	0809BE and later	1.28AE and later	0811BE and later		*3
GX Configurator-FL	1.25AB and later	0806BB and later	1.25AB and later	0806BB and later		*3
GX Configurator-PT	1.25AB and later	0806BB and later	1.25AB and later	0806BB and later		*3
GX Configurator-AS	1.23Z and later	0806BZ and later	1.23Z and later	0806BZ and later		*3
GX Configurator-SC	2.21X and later	0911BX and later	2.21X and later	1001BX and later		*3
GX Configurator-QP	2.34L and later	1004BL and later	2.34L and later	1004BL and later		
GX Configurator-AP	1.19V and later	0804BV and later	1.19V and later	0804BV and later		
GX Configurator-MB	1.09K and later	0806BK and later	1.09K and later	0806BK and later		*3
GX Simulator	7.25B and later	0912BB and later	7.25B and later	0912BB and later		*3
GX Converter	2.25B and later	0710BB and later	1.22Y and later	0804BB and later		*3, *4
MX Component	3.14Q and later	1005BQ and later	3.14Q and later	1005BQ and later		
MX Sheet	1.10L and later	1005BL and later	1.10L and later	1005BL and later		
MX MESInterface	1.06G and later	1009BG and later	1.06G and later	1009BG and later		
PX Developer	1.25B and later	1005BB and later	1.28E and later	1012BE and later	*5	
PX Developer Monitor Tool	1.28E and later	1012BE and later	1.28E and later	1012BE and later		
GT Works3	1.15R and later	1003AR and later	1.14Q and later	1004AQ and later		
GT Works2/GT Designer2	2.103H and later	1004AH and later	2.103H and later	1005AH and later	*6	
GX LogViewer	1.03D and later	—	1.05F and later	—	Section 2.3	
LCPU Logging Configuration Tool	1.05F and later	—	1.07H and later	—		
A/QnA to Q conversion support tool	1.04 and later	—	1.04 and later	—		

\*1: Note the operating environment (CPU performance, required memory, monitor resolution) for each product.

\*2: "DATE" is printed on the front right of CD-ROM or DVD-ROM.

- The first four digits indicate the year and month of manufacture.
- The last two digits indicate the H/W version or the S/W version.
- S/W versions are described using alphabets repeatedly from A to Z.

\*3: Use the products after installing GX Developer. For details of the operating environment, refer to the following.

\*4: Add-in software for Microsoft® Word and Microsoft® Excel are not compatible with Windows® 7.

\*5: GX Developer is required for Programming Tool. For details of the operating environment, refer to the following.

\*6: Only GT Designer2 is compatible of the software packages included in the CD-ROMs.



HEAD OFFICE : TOKYO BUILDING, 2-7-3 MARUNOUCHI, CHIYODA-KU, TOKYO 100-8310, JAPAN  
NAGOYA WORKS : 1-14, YADA-MINAMI 5-CHOME, HIGASHI-KU, NAGOYA, JAPAN

# TECHNICAL BULLETIN

[Issue No.] FA-A-0091-F

[Page] 3/24

[Title] Products compatible with Windows 7 and precautions for installation

[Date of Issue] June 2010 (Ver.F: January 2012)

[Relevant Models] Mitsubishi integrated FA software MELSOFT series  
GX series, MX series, PX series, GT series

(2) Windows<sup>®</sup> 7 (64-bit) compatible products

Product #1	Japanese Version		English Version		Reference	Remarks
	S/W Version	DATE of CD-ROM or DVD-ROM #2	S/W Version	DATE of CD-ROM or DVD-ROM #2		
iQ Works	1.24A and later	1108CA and later	Future compatibility	—	Section 2.2	
GX Works2	1.56J and later	1105BJ and later	1.62Q and later	1107BQ and later		
GX Developer	8.98C and later	1104BC and later	8.98C and later	1104BC and later		
GX Configurator-AD	2.12N and later	1006BN and later	2.11M and later	1001BM and later		*3
GX Configurator-DA	2.11M and later	0911BM and later	2.11M and later	1001BM and later		*3
GX Configurator-CT	1.29AF and later	1001BF and later	1.29AF and later	1003BF and later		*3
GX Configurator-TC	1.24AA and later	0806BA, 0807BA and later	1.24AA and later	0806BA, 0807BA and later		*3
GX Configurator-TI	1.28AE and later	0809BE and later	1.28AE and later	0811BE and later		*3
GX Configurator-FL	1.25AB and later	0806BB and later	1.25AB and later	0806BB and later		*3
GX Configurator-PT	1.25AB and later	0806BB and later	1.25AB and later	0806BB and later		*3
GX Configurator-AS	1.23Z and later	0806BZ and later	1.23Z and later	0806BZ and later		*3
GX Configurator-SC	2.21X and later	0911BX and later	2.21X and later	1001BX and later		*3
GX Configurator-QP	2.35M and later	1104BM and later	2.35M and later	1104BM and later		Section 2.1
GX Configurator-AP	1.19V and later	0804BV and later	1.19V and later	0804BV and later		
GX Configurator-MB	1.09K and later	0806BK and later	1.09K and later	0806BK and later	*3	
GX Simulator	7.27D and later	1010BD and later	7.27D and later	1010BD and later	*3	
GX Converter	2.25B and later	0710BB and later	1.22Y and later	0804BB and later	*3, *4	
MX Component	3.15R and later	1105BR and later	3.15R and later	1105BR and later		
MX Sheet	1.11M and later	1105BM and later	1.11M and later	1105BM and later		
MX MESInterface	1.08J and later	1109BJ and later	1.08J and later	1109BJ and later	*5	
PX Developer	1.31H and later	1107BH and later	1.31H and later	1110BH and later	*6	
PX Developer Monitor Tool	1.31H and later	1107BH and later	1.31H and later	1110BH and later		
GT Works3	1.30G and later	1104AG and later	1.31H and later	1107AH and later	Section 2.2	
GT Works2/GT Designer2	—	—	—	—	—	
GX LogViewer	1.10L and later	—	1.10L and later	—	Section 2.3	
LCPU Logging Configuration Tool	1.18U and later	—	1.18U and later	—		
A/QnA to Q conversion support tool	1.05 and later	—	1.05 and later	—		

\*1: Note the operating environment (CPU performance, required memory, monitor resolution) for each product.

\*2: "DATE" is printed on the front right of CD-ROM or DVD-ROM.

- The first four digits indicate the year and month of manufacture.
- The last two digits indicate the H/W version or the S/W version.
- S/W versions are described using alphabets repeatedly from A to Z.

\*3: Use the products after installing GX Developer. For details of the operating environment, refer to the following.

\*4: Add-in software for Microsoft<sup>®</sup> Word and Microsoft<sup>®</sup> Excel are not compatible with Windows<sup>®</sup> 7.

\*5: Among the software packages included in the CD-ROM, DB Connection Service and DB Connection Service Setting Tool are supported by software version 1.06G and later.

\*6: GX Developer is required for Programming Tool. For details of the operating environment, refer to the following.