## **Plug-in Signal Conditioners M-UNIT**


## ANALOG SWITCHING MODULE

#### **Functions & Features**

- · Selecting one signal as output from up to four analog input signals
- Distributing a single input signal to any or all of the up to four output channels
- High-density mounting

#### **Typical Applications**

- Switching 1 5 V DC signal: no contact failure that happens when using mechanical contacts for this purpose
- Switching low-speed pulse signals
- Switching alternating signals



# MODEL: MNV-[1]-[2][3]

### **ORDERING INFORMATION**

- Code number: MNV-[1]-[2][3]
- Specify a code from below for each of [1] through [3]. (e.g. MNV-1-B/Q)
- · Specify the specification for option code /Q (e.g. /C01/S01)

# [1] SWITCHING CIRCUIT

1: Single circuit 2: Double circuit

# [2] POWER INPUT

### **AC Power**

B: 100 V AC C: 110 V AC **D**: 115 V AC F: 120 V AC G: 200 V AC **H**: 220 V AC : 240 V AC **DC Power** S: 12 V DC

MSYSTEM M-SYSTEM CO., LTD.



R: 24 V DC V: 48 V DC

# [3] OPTIONS

blank: none /Q: With options (specify the specification)

#### **SPECIFICATIONS OF OPTION:** Q (multiple selections)

COATING (For the detail, refer to M-System's web site.) /C01: Silicone coating /C02: Polyurethane coating /C03: Rubber coating **TERMINAL SCREW MATERIAL** /S01: Stainless steel

## **GENERAL SPECIFICATIONS**

Construction: Plug-in Connection: M3.5 screw terminals Screw terminal: Chromated steel (standard) or stainless steel Housing material: Flame-resistant resin (black) Switching: Photo MOSFET relay Isolation: Switching command relay to signal line to power Monitor LED 1: Red light turns on with SW1 ON Monitor LED 2: Red light turns on with SW2 ON Monitor LED 3: Red light turns on with SW3 ON Monitor LED 4: Red light turns on with SW4 ON

## **INPUT & OUTPUT**

#### Signal Line

Max. operational voltage range: ±50 V DC (min. span 10 mV) Max. operational current range: ±50 mA DC

Max. operational frequency range: 100 Hz **ON resistance**: Approx. 50  $\Omega$  per line Switching Command: Relay contact or open collector

Sensing:

Approx. 20 V DC @ 7 mA with single circuit Approx. 20 V DC @ 14 mA with double circuit **Detection levels ON resistance**:  $\leq 1 \text{ K}\Omega, \leq 5 \text{ V}$ **OFF resistance**:  $\geq 100 \text{ k}\Omega$ ,  $\geq 18 \text{ V}$ Leakage current at OFF: 1 µA (400 V AC between lines)

## **INSTALLATION**

#### Power input


- AC: Operational voltage range: rating ±10 %,
- 50/60 ±2 Hz, approx. 2 VA
- •DC: Operational voltage range: rating  $\pm 10$  %

(ripple 10 % p-p max.) approx. 1 W (30 mA at 24 V) Operating temperature: -5 to +60°C (23 to 140°F) Operating humidity: 30 to 90 %RH (non-condensing) Mounting: Surface or DIN rail Weight: 350 g (0.77 lb)


#### PERFORMANCE

Response time: Approx. 1 msec. Leakage current at open circuit:  $\leq 1 \mu A$ Insulation resistance:  $\geq 100 M\Omega$  with 500 V DC Dielectric strength: 1500 V AC @ 1 minute (switching command relay to singal line to power to ground)

### EXTERNAL VIEW




### **EXTERNAL DIMENSIONS & TERMINAL ASSIGNMENTS unit: mm (inch)**



• When mounting, no extra space is needed between units.



### SCHEMATIC CIRCUITRY & CONNECTION DIAGRAM



Specifications are subject to change without notice.



 $\mathbb{N}$